

2.13inch e-Paper (G) V2

User Manual



Revision History

Version	Content	Date	Page
1.0	New creation	2025/05/15	All



Contents

1. OVERVIEW	1
2. FEATURES	2
3. MECHANICAL SPECIFICAITONS	3
4. MECHANICAL DRAWING OF EPD MODULE	4
5. PIN ASSIGNMENT	5
6. ELECTRICAL CHARACTERISTICS	6
6.1 ABSOLUTE MAXIMUM RATING	6
6.2 PANEL DC CHARACTERISTICS	7
6.3 PANEL AC CHARACTERISTICS	8
6.3.1 MCU Interface Selection	8
6.3.2 MCU Serial Interface (4-wire SPI).....	8
6.3.3 MCU Serial Interface (3-wire SPI)	9
7. COMMAND TABLE.....	10
8. OPTICAL SPECIFICATIONS.....	31
9. TYPICAL APPLICATION CIRCUIT	32
10. RELIABILITY TEST.....	33
11. INSPECTION METHOD AND CONDITION	34
11.1 INSPECTION CONDITION.....	34
11.2 ZONE DEFINITION.....	34
11.3 GENERAL INSPECTION STANDARDS FOR PRODU.....	35
11.3.1 APPEARANCE INSPECTION STANDARDS Selection.....	35
12. HANDLING, SAFETY, AND ENVIRONMENTAL REQUIREMENTS.....	38
13. PRECATIONS.....	39

1. OVERVIEW

The display is a reflective electrophoretic technology display module on an active matrix TFT substrate. The panel is capable of displaying black, white, yellow and red images depending on the associated lookup table used. The circuitry on the panel includes an integrated gate and source driver, timing controller, oscillator, DC-DC boost circuit, and memory to store the frame buffer and lookup tables, and additional circuitry to control VCOM and BORDER settings.




2. FEATURES

- ✧ Highlight Red and Yellow color
- ✧ High contrast
- ✧ High reflectance
- ✧ Ultra-wide viewing angle
- ✧ Ultra-low power consumption
- ✧ Pure reflective mode
- ✧ Bi-stable display
- ✧ Antiglare hard-coated front-surface
- ✧ Low current deep sleep mode
- ✧ On-chip display RAM
- ✧ Waveform stored in On-chip OTP
- ✧ Serial peripheral interface available
- ✧ On-chip oscillator
- ✧ On-chip booster and regulator control for generating VCOM, Gate and Source driving voltage
- ✧ I2C signal master interface to read external temperature sensor
- ✧ Available in COG package

3. MECHANICAL SPECIFICATIONS

Parameter	Specifications	Unit	Remark
Screen Size	2.13	Inch	
Display Resolution	250(H)×122(V)	Pixel	DPI:130
Active Area	48.55×23.7046	mm	
Pixel Pitch	0.1943×0.1942	mm	
Pixel Configuration	Rectangle		
Outline Dimension	59.2(H)×29.2(V)×1.0(D)	mm	
Weight	3.3±0.5	g	

4. MECHANICAL DRAWING OF EPD MODULE



5. PIN ASSIGNMENT

NO.	Name	I/O	Description	Remark
1	NC		Do not connect with other NC pins	Keep open
2	GDR	O	This pin is N-MOS gate control	
3	RESE	P	Current sense input for control loop	
4	NC		Do not connect with other NC pins	Keep open
5	VSPL	P	Positive source voltage	
6	TSCL	I/O	I2C clock for external temperature sensor (I2C interface need external pull high resistance) Must pull high or low if not used (Default low)	
7	TSDA	I/O	I2C data for external temperature sensor (I2C interface need external pull high resistance) Must pull high or low if not used (Default low)	
8	BS	I	Input interface setting	
9	BUSY_N	O	This pin indicates the driver status	
10	RST_N	I	Global reset pin. Low reset (normal pull high)	
11	DC	I	Serial communication Command/Data input	
12	CSB	I	Serial communication chip select	
13	SCL	I	Serial communication clock input	
14	SDA	I/O	Serial communication data input	
15	VDDIO	P	IO voltage supply	
16	VDD	P	Digital/Analog power	
17	VSS	P	Digital ground	
18	VDD_15V	P	1.5V voltage input & output	
19	VMTP	P	MTP program power	
20	VSP	P	Positive source voltage	
21	VGP	P	Positive gate voltage	
22	VSN	P	Negative source voltage	
23	VGN	P	Negative gate voltage	
24	VCOM	P	VCOM output	

Note:

I: Input, O: Output, P: Power, D: Dummy, S: Short circuit, M: Mark, PI: Power input, PO: Power output, I/O: Input / Output, PS: Power Setting, C: Capacitor pin.

6. ELECTRICAL CHARACTERISTICS

6.1 ABSOLUTE MAXIMUM RATING

Parameter	Symbol	Rating	Unit
Logic supply voltage	$V_{DD}, V_{DDIO}, V_{DD1}, V_{PP}$	-0.3 to +6.0	V
Digital input voltage	V_{IN}	-0.3 to $V_{DDIO} + 0.3$	V
Operating Temp range	T_{OPR}	0 to +40	°C
Storage Temp range	T_{STG}	-25 to +70	°C
Optimal Storage Humidity	H_{STGO}	55±10	%RH

Note:


Absolute Maximum Ratings are stress ratings. Stresses in excess of these ratings can cause permanent damage to the device. Functional operation of the device at these or any other conditions beyond those indicated in the operational sections of this data sheet is not implied. Exposing device to the absolute maximum ratings in a long period of time may degrade the device and affect its reliability.

6.2 PANEL DC CHARACTERISTICS

Parameter	Symbol	Condition	Applicable pin	Min.	Typ.	Max.	Unit
Single ground	V_{SS}	-	-	-	0	-	V
Logic supply voltage	V_{DD}	-	VDD	2.3	3.0	3.6	V
Core logic voltage	V_{IO}	-	VIO	2.3	3.0	3.6	V
High level input voltage	V_{IH}	-	-	$0.7V_{IO}$	-	V_{IO}	V
Low level input voltage	V_{IL}	-	-	GND	-	$0.3V_{DD}$	V
High level output voltage	V_{OH}	$I_{OH} = 400 \mu A$	-	$V_{IO}-0.4$	-	-	V
Low level output voltage	V_{OL}	$I_{OL} = -400 \mu A$	-	GND	-	$GND+0.4$	V
Typical power	P_{TYP}	$V_{DD}=3.3V$	-	-	9.9	-	mW
Deep sleep mode	P_{STPY}	$V_{DD}=3.3V$	-	-	0.003	-	mW
Typical operating current	I_{opr_VDD}	$V_{DD}=3.3V$	-	-	3.0	-	mA
Fall/Fast update time	-	25°C	-	-	16/11	-	sec
Stand-by current	I_{st_VDD}		-	-	1	5	μA

Notes:

6-2-1: The typical power is measured with following transition from horizontal 4 scale pattern to vertical 4 scale pattern.



6-2-2: The deep sleep power is the consumed power when the panel controller is in deep sleep mode.

6-2-3: The listed electrical/optical characteristics are only guaranteed under the controller & waveform provided by Waveshare.

6-2-4: Electrical measurement: Multimeter.

6.3 PANEL AC CHARACTERISTICS

6.3.1 MCU Interface Selection


The 3-wire/4-wire serial port as communication interface for all the function and command setting.

The 3-wire/4-wire engine act as a “slave mode” for all the time, and will not issue any command to the 3-wire/4-wire bus itself.


Under read mode, 3-wire/4-wire engine will return the data during “Data phase”.

The returned data should be latched at the rising edge of SCL by external controller. Data in the “Hi-Z phase” will be ignored by 3-wire/4-wire engine during write operation, and should be ignored during read operation also. During read operation, external controller should float SDA pin under “Hi-Z phase” and “Data phase”.


6.3.2 MCU Serial Interface (4-wire SPI)




4 pin serial interface characteristics(write mode)




4 pin serial interface characteristics(read mode)




6.3.3 MCU Serial Interface (3-wire SPI)



3 pin serial interface characteristics (write mode)



3 pin serial interface characteristics (read mode)



7. COMMAND TABLE

Address	command	Bit										
		R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
R00H	Panel setting (PSR)	W	0	0	0	0	0	0	0	0	0	00H
		W	1	RES[1]	RES[0]	PST_MODE	-	UD	SHL	SHD_N	RST_N	0Fh
		W	1	LUT_EN	-	FOPT	VCMZ	TS_AUTO	TIEG	NORG	VC_LUTZ	09h
R01H	Power setting (PWR)	W	0	0	0	0	0	0	0	0	1	01H
		W	1	-	-	-	-	-	VSC_EN	VDS_EN	VDG_EN	07h
		W	1	-	-	-	-	-	-	VGPN [1]	VGPN [0]	00h
		W	1	-	VSPL_0[6]	VSPL_0[5]	VSPL_0[4]	VSPL_0[3]	VSPL_0[2]	VSPL_0[1]	VSPL_0[0]	00h
		W	1	-	VSP_1[6]	VSP_1 [5]	VSP_1 [4]	VSP_1 [3]	VSP_1 [2]	VSP_1 [1]	VSP_1 [0]	00h
		W	1	-	VSPL_1[6]	VSPL_1[5]	VSPL_1[4]	VSPL_1[3]	VSPL_1[2]	VSPL_1[1]	VSPL_1[0]	00h
		W	1	-	VSN_1[6]	VSN_1[5]	VSN_1[4]	VSN_1[3]	VSN_1[2]	VSN_1[1]	VSN_1[0]	00h
		W	1	-	VSPL_1[6]	VSPL_1[5]	VSPL_1[4]	VSPL_1[3]	VSPL_1[2]	VSPL_1[1]	VSPL_1[0]	00h
R02H	Power OFF(POF)	W	0	0	0	0	0	0	0	1	0	02H
		W	1	-	-	-	-	-	-	-	-	00h
R04H	Power ON (PON)	W	0	0	0	0	0	0	1	0	0	04H
R06H	Booster Soft Start (BTST)	W	0	0	0	0	0	0	1	1	0	06H
		W	1	-	-	-	-	PHB_SFT[1:0]	PHA_SFT[1:0]			00h
		W	1	-	-	PHA_ON[5:0]						02h
		W	1	-	-	PHA_OFF[5:0]						07h
		W	1	-	-	PHB_ON[5:0]						02h
		W	1	-	-	PHB_OFF[5:0]						07h
		W	1	-	-	PHC_ON[5:0]						02h
		W	1	-	-	PHC_OFF[5:0]						07h
R07H	Deep Sleep(DSLP)	W	0	0	0	0	0	0	1	1	1	07H
		W	1	1	0	1	0	0	1	0	1	A5h
R10H	Data Start transmission (DTM)	W	0	0	0	0	1	0	0	0	0	10H
		W	1	#	#	#	#	#	#	#	#	00H
R11H	Data Stop (DSP)	W	0	0	0	0	1	0	0	0	1	11H
		R	1	Data_flag	-	-	-	-	-	-	-	--
R12H	Display Refresh (DRF)	W	0	0	0	0	1	0	0	1	0	12H
		W	1	-	-	-	-	-	-	-	-	00H
R17H	Auto sequence (AUTO)	W	0	0	0	0	1	0	1	1	1	17H
		W	1	Code[7]	Code[6]	Code[5]	Code[4]	Code[3]	Code[2]	Code[1]	Code[0]	A5h
R30H	PLL control (PLL)	W	0	0	0	1	1	0	0	0	0	30H
		W	1	-	-	-	-	Dyna	FR[2:0]			02h
R40H	Temperature Sensor Command (TSC)	W	0	0	1	0	0	0	0	0	0	40H
		R	1	D10/TS[7]	D9/TS[7]	D8/TS[6]	D7/TS[5]	D6/TS[4]	D5/TS[3]	D4/TS[2]	D3/TS[1]	--
R41H	Temperature Sensor Calibration (TSE)	R	1	D2/ TS[9]	D1/TS[8]	D0	-	-	-	-	-	--
		W	0	0	1	0	0	0	0	0	1	41H
R42H	Temperature Sensor Write (TSW)	W	1	TSE	-	-	TO[4]	TO[3]	TO[2]	TO[1]	TO[0]	00h
		W	0	0	1	0	0	0	0	1	0	42H
		W	1	WATTR[7]	WATTR[6]	WATTR[5]	WATTR[4]	WATTR[3]	WATTR[2]	WATTR[1]	WATTR[0]	00h
		W	1	WMSB[7]	WMSB[6]	WMSB[5]	WMSB[4]	WMSB[3]	WMSB[2]	WMSB[1]	WMSB[0]	00h
R43H	Temperature Sensor Read (TSR)	W	1	WLSB[7]	WLSB[6]	WLSB[5]	WLSB[4]	WLSB[3]	WLSB[2]	WLSB[1]	WLSB[0]	00h
		W	0	0	1	0	0	0	0	1	1	43H
		R	1	RMSB[7]	RMSB[6]	RMSB[5]	RMSB[4]	RMSB[3]	RMSB[2]	RMSB[1]	RMSB[0]	--
		R	1	RLSB[7]	RLSB[6]	RLSB[5]	RLSB[4]	RLSB[3]	RLSB[2]	RLSB[1]	RLSB[0]	--
R50H	VCOM and DATA interval setting (CDI)	W	0	0	1	0	1	0	0	0	0	50H
		W	1	VBD[2]	VBD[1]	VBD[0]	DDX	CDI[3]	CDI[2]	CDI[1]	CDI[0]	97h

R51H	Lower Power Detection (LPD)	W	0	0	1	0	1	0	0	0	1	51H
		R	1	-	-	-	-	-	-	-	LPD	--
R61H	Resolution setting(TRES)	W	0	0	1	1	0	0	0	0	1	61H
		W	1	-	-	-	-	-	-	HRES(9)	HRES(8)	00h
		W	1	HRES(7)	HRES(6)	HRES(5)	HRES(4)	HRES(3)	HRES(2)	0	0	00h
		W	1	-	-	-	-	-	-	VRES(9)	VRES(8)	00h
		W	1	VRES(7)	VRES(6)	VRES(5)	VRES(4)	VRES(3)	VRES(2)	VRES(1)	VRES(0)	00h
R65H	Gate/Source Start Setting(GSST)	W	0	0	1	1	0	0	1	0	1	65H
		W	1	-	-	-	-	-	-	S_start(9)	S_start(8)	00h
		W	1	S_start(7)	S_start(6)	S_start(5)	S_start(4)	S_start(3)	S_start(2)	0	0	00h
		W	1	-	-	-	-	-	-	G_start(9)	G_start(8)	00h
		W	1	G_start(7)	G_start(6)	G_start(5)	G_start(4)	G_start(3)	G_start(2)	G_start(1)	G_start(0)	00h
R70H	REVISION (REV)	W	0	0	1	1	1	0	0	0	0	70H
		R	1	0	0	0	0	1	0	0	1	09h
		R	1	0	0	0	0	0	0	1	0	02h
		R	1	0	0	0	0	0	0	0	1	01h
R80H	Auto Measure Vcom (AMV)	W	0	1	0	0	0	0	0	0	0	80 H
		W	1	P[1]	P[0]	AMVT[1]	AMVT[0]	XON	AMVS	AMV	AMVE	00h
R81H	Vcom Value (VV)	W	0	1	0	0	0	0	0	0	1	81H
		R	1	-	VV[6]	VV[5]	VV[4]	VV[3]	VV[2]	VV[1]	VV[0]	--
R82H	Vcom_DC Setting register(VDCS)	W	0	1	0	0	0	0	0	1	0	82H
		W	1	-	VDCS[6]	VDCS[5]	VDCS[4]	VDCS[3]	VDCS[2]	VDCS[1]	VDCS[0]	00h
R83H	Partial Window (PTLW)	W	0	1	0	0	0	0	0	1	1	83H
		W	1	-	-	-	PTH_ENB	-	-	HRST(9)	HRST(8)	00h
		W	1	HRST(7)	HRST(6)	HRST(5)	HRST(4)	HRST(3)	HRST(2)	0	0	00h
		W	1	-	-	-	-	-	-	HRED(9)	HRED(8)	00h
		W	1	HRED(7)	HRED(6)	HRED(5)	HRED(4)	HRED(3)	HRED(2)	0	0	00h
		W	1	-	-	-	-	-	-	VRST(9)	VRST(8)	00h
		W	1	VRST(7)	VRST(6)	VRST(5)	VRST(4)	VRST(3)	VRST(2)	VRST(1)	VRST(0)	00h
		W	1	-	-	-	-	-	-	VRST(9)	VRST(8)	00h
		W	1	VRST(7)	VRST(6)	VRST(5)	VRST(4)	VRST(3)	VRST(2)	VRST(1)	VRST(0)	00h
		W	1	-	-	-	-	-	-	-	PMOD	00h
R90H	Program mode(PGM)	W	0	1	0	0	1	0	0	0	0	90H
R91H	Active Program(APG)	W	0	1	0	0	1	0	0	0	1	91H
R92H	Read MTP data (RMTP)	W	0	1	0	0	1	0	0	1	0	92H
		R	1	#	#	#	#	#	#	#	#	-
RA2H	MTP Program Config Register(PGM_CFG)	W	0	1	0	1	0	0	0	1	0	A2H
		W	1	-	-	-	VMTPSEL	-	-	M_dis	S_dis	00h
		W	1	PGM_SADDR[15:8]								00h
		W	1	PGM_SADDR[7:0]								00h
		W	1	PGM_DSIZE[15:8]								0Fh
		W	1	PGM_DSIZE[7:0]								00h
RE0H	CASCADE setting (CCSET)	W	0	1	1	1	0	0	0	0	0	E0H
		W	1	-	-	-	-	-	-	TSFIX	CCEIN	00h
RE3H	Power saving(PWS)	W	0	1	1	1	0	0	0	1	1	E3H
		W	1	VCOM_W[3]	VCOM_W[2]	VCOM_W[1]	VCOM_W[0]	SD_W[3]	SD_W[2]	SD_W[2]	SD_W[0]	00h
RE4H	LVD voltage Select(LVSEL)	W	0	1	1	1	0	0	1	0	0	E4H
		W	1	-	-	-	-	-	-	LVD_SEL[1]	LVD_SEL[0]	03h
RE5H	CASCADE setting select (CCS_SEL)	W	0	1	1	1	0	0	1	0	1	E5H
		W	1	-	-	-	-	cascade_syn	-	-	-	00h

R00H		Bit									
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
PSR	W	0	0	0	0	0	0	0	0	0	00H
1 st Parameter	W	1	RES[1]	RES[0]	PST_MODE	-	UD	SHL	SHD_N	RST_N	0Fh
2 nd Parameter	W	1	LUT_EN	-	FOPT	VCMZ	TS_AUTO	TIEG	NORG	VC_LUTZ	09h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as :		
	1 st parameter		
	Bit	Name	Description
	0	RST_N	RST_N function 1: no effect. (default) 0: Booster OFF, Register data are set to their default values, and Source/Border/Vcom: floating
	1	SHD_N	SHD_N function 0 : Booster OFF, register data are kept, and Source / Border / Vcom are kept 0V or floating. 1 : Booster on. (default)
	2	SHL	SHL function 0: Shift left; First data=Sn→Sn-1 →...→S2→Last data=S1. 1: Shift right; First data=S1→S2 →...→Sn-1→Last data=Sn. (default)
	3	UD	UD function 0:Scan down; First line=Gn→Gn-1 →...→G2→Last line=G1. 1:Scan up; First line=G1→G2 →...→Gn-1→Last line=Gn. (default)
	5	PST_MODE	Power switch operation mode 0:Power switching time in the period of frame scanning.(default) 1:Power switching time in the external period before frame scanning.
	7-6	RES[1,0]	Resolution setting 00: Display resolution is 128x250(default) 01: Display resolution is 96x250 10: Display resolution is 64x250 11: Display resolution is 32x250

	2 nd parameter		
	Bit	Name	Description
	0	VC_LUTZ	VCOM status function 0 : No effect 1 : After refreshing display, the output of VCOM is set to floating automatically (default)
	1	NORG	VCOM status function 0 : No effect (default) 1 : After refreshing display, VCOM is tied to GND before power off
	2	TIEG	VGN power off status function 0 : No effect (default) 1 : Power off, VGN will be tied to GND
	3	TS_AUTO	Temperature sensing will be activated automatically one time 0 : Before enabling booster, Temperature Sensor will be activated automatically one time. 1 : When RST_N low to high, Temperature Sensor will be activated automatically one time. (default)
	4	VCMZ	VCOM status function 0 : No effect (default) 1 : VCOM is always floating
	5	FOPT	FOPT function 0: Scan 1 frame after waveform finished(default) 1: No scan after waveform finished and switch the source channel output to Hiz.
	7	LUT_EN	LUT selection setting 0 : Using LUT from MTP(default) 1 : Using LUT from register

Priority of VCOM setting: VCMZ > NORG > FOPT > VC_LUTZ

FOPT setting is part of refreshing display.
FOPT: Power off floating.

Notes:

1. Non-select gate line keep at VGN for DSP/DRF and AMV
2. Dummy source line follow LUTC for DSP/DRF
3. When SHD_N become low, DCDC will turn off. Register and SRAM data will keep until VDD turn off. SD output and VCOM will base on previous condition. It may have two condition: 0V or floating.
4. When RST_N become low, driver will reset. All register will reset to default value. All of the driver's functions will disable. Source/Gate/Border/VCOM will be released to floating

R01H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
PWR	W	0	0	0	0	0	0	0	0	1	01h
1 st Parameter	W	1	-	-	-	-	-	VSC_EN	VDS_EN	VDG_EN	07h
2 nd Parameter	W	1	-	-	-	-	-	-	VGPN [1]	VGPN [0]	00h
3 rd Parameter	W	1	-	VSPL_0 [6:0]							00h
4 th Parameter	W	1	-	VSP_1 [6:0]							00h
5 th Parameter	W	1	-	VSN_1 [6:0]							00h
6 th Parameter	W	1	-	VSPL_1 [6:0]							00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as :		
	1 st Parameter:		
	Bit	Name	Description
	0	VDG_EN	Gate power selection. 0 : External gate power from VGP/VGN pins. 1 : Internal DDCDC function for generate VGP/VGN. (default)
	1	VDS_EN	Source power selection. 0 : External source power from VSP/VSN pins. 1 : Internal regulator function for generate VSP/VSN (default)
	2	VSC_EN	Source LV power selection. 0 : External source power from VSPL pins. 1 : Internal regulator function for generate VSPL (default)
	2nd Parameter:		
	Bit	Name	Description
	1-0	VGPN	VGPN Voltage Level. 00: VGP=20 v, VGN=-20v (default) 01: VGP=17 v, VGN=-17v 10: VGP=15 v, VGN=-15v 11: VGP=10 v, VGN=-10v

3rd & 4th & 6th Parameter: Internal VSP_1/VSPL_0/ VSPL_1 power selection										
Bit	Name	Description								
6-0	VSP_1 & VSPL_0 & VSPL_1	Internal VSP & VSPL power selection.								
		bit[6:0]		Voltage(V)	bit [6:0]		Voltage(V)	bit [6:0]		Voltage(V)
		0000000	00h	3	0101001	29h	7.1	1010010	52h	11.2
		0000001	01h	3.1	0101010	2Ah	7.2	1010011	53h	11.3
		0000010	02h	3.2	0101011	2Bh	7.3	1010100	54h	11.4
		0000011	03h	3.3	0101100	2Ch	7.4	1010101	55h	11.5
		0000100	04h	3.4	0101101	2Dh	7.5	1010110	56h	11.6
		0000101	05h	3.5	0101110	2Eh	7.6	1010111	57h	11.7
		0000110	06h	3.6	0101111	2Fh	7.7	1011000	58h	11.8
		0000111	07h	3.7	0110000	30h	7.8	1011001	59h	11.9
		0001000	08h	3.8	0110001	31h	7.9	1011010	5Ah	12
		0001001	09h	3.9	0110010	32h	8	1011011	5Bh	12.1
		0001010	0Ah	4	0110011	33h	8.1	1011100	5Ch	12.2
		0001011	0Bh	4.1	0110100	34h	8.2	1011101	5Dh	12.3
		0001100	0Ch	4.2	0110101	35h	8.3	1011110	5Eh	12.4
		0001101	0Dh	4.3	0110110	36h	8.4	1011111	5Fh	12.5
		0001110	0Eh	4.4	0110111	37h	8.5	1100000	60h	12.6
		0001111	0Fh	4.5	0111000	38h	8.6	1100001	61h	12.7
		0010000	10h	4.6	0111001	39h	8.7	1100010	62h	12.8
		0010001	11h	4.7	0111010	3Ah	8.8	1100011	63h	12.9
		0010010	12h	4.8	0111011	3Bh	8.9	1100100	64h	13
		0010011	13h	4.9	0111100	3Ch	9	1100101	65h	13.1
		0010100	14h	5	0111101	3Dh	9.1	1100110	66h	13.2
		0010101	15h	5.1	0111110	3Eh	9.2	1100111	67h	13.3
		0010110	16h	5.2	0111111	3Fh	9.3	1101000	68h	13.4
		0010111	17h	5.3	1000000	40h	9.4	1101001	69h	13.5
		0011000	18h	5.4	1000001	41h	9.5	1101010	6Ah	13.6
		0011001	19h	5.5	1000010	42h	9.6	1101011	6Bh	13.7

0011010	1Ah	5.6	1000011	43h	9.7	1101100	6Ch	13.8
0011011	1Bh	5.7	1000100	44h	9.8	1101101	6Dh	13.9
0011100	1Ch	5.8	1000101	45h	9.9	1101110	6Eh	14
0011101	1Dh	5.9	1000110	46h	10	1101111	6Fh	14.1
0011110	1Eh	6	1000111	47h	10.1	1110000	70h	14.2
0011111	1Fh	6.1	1001000	48h	10.2	1110001	71h	14.3
0100000	20h	6.2	1001001	49h	10.3	1110010	72h	14.4
0100001	21h	6.3	1001010	4Ah	10.4	1110011	73h	14.5
0100010	22h	6.4	1001011	4Bh	10.5	1110100	74h	14.6
0100011	23h	6.5	1001100	4Ch	10.6	1110101	75h	14.7
0100100	24h	6.6	1001101	4Dh	10.7	1110110	76h	14.8
0100101	25h	6.7	1001110	4Eh	10.8	1110111	77h	14.9
0100110	26h	6.8	1001111	4Fh	10.9	1111000	78h	15
0100111	27h	6.9	1010000	50h	11	other	15	
0101000	28h	7	1010001	51h	11.1			

5th Parameter: Internal VSN_1 power selection

Bit	Name	Description					
6-0	VSN_1	Internal VSN power selection.					
		bit[6:0]	Voltage(V)	bit [6:0]	Voltage(V)	bit [6:0]	Voltage(V)
		0000000	00h -3	0101001	29h -7.1	1010010	52h -11.2
		0000001	01h -3.1	0101010	2Ah -7.2	1010011	53h -11.3
		0000010	02h -3.2	0101011	2Bh -7.3	1010100	54h -11.4
		0000011	03h -3.3	0101100	2Ch -7.4	1010101	55h -11.5
		0000100	04h -3.4	0101101	2Dh -7.5	1010110	56h -11.6
		0000101	05h -3.5	0101110	2Eh -7.6	1010111	57h -11.7
		0000110	06h -3.6	0101111	2Fh -7.7	1011000	58h -11.8
		0000111	07h -3.7	0110000	30h -7.8	1011001	59h -11.9
		0001000	08h -3.8	0110001	31h -7.9	1011010	5Ah -12
		0001001	09h -3.9	0110010	32h -8	1011011	5Bh -12.1
		0001010	0Ah -4	0110011	33h -8.1	1011100	5Ch -12.2
		0001011	0Bh -4.1	0110100	34h -8.2	1011101	5Dh -12.3
		0001100	0Ch -4.2	0110101	35h -8.3	1011110	5Eh -12.4
		0001101	0Dh -4.3	0110110	36h -8.4	1011111	5Fh -12.5
		0001110	0Eh -4.4	0110111	37h -8.5	1100000	60h -12.6
		0001111	0Fh -4.5	0111000	38h -8.6	1100001	61h -12.7
		0010000	10h -4.6	0111001	39h -8.7	1100010	62h -12.8
		0010001	11h -4.7	0111010	3Ah -8.8	1100011	63h -12.9
		0010010	12h -4.8	0111011	3Bh -8.9	1100100	64h -13
		0010011	13h -4.9	0111100	3Ch -9	1100101	65h -13.1
		0010100	14h -5	0111101	3Dh -9.1	1100110	66h -13.2
		0010101	15h -5.1	0111110	3Eh -9.2	1100111	67h -13.3
		0010110	16h -5.2	0111111	3Fh -9.3	1101000	68h -13.4
		0010111	17h -5.3	1000000	40h -9.4	1101001	69h -13.5
		0011000	18h -5.4	1000001	41h -9.5	1101010	6Ah -13.6
		0011001	19h -5.5	1000010	42h -9.6	1101011	6Bh -13.7
		0011010	1Ah -5.6	1000011	43h -9.7	1101100	6Ch -13.8
		0011011	1Bh -5.7	1000100	44h -9.8	1101101	6Dh -13.9
		0011100	1Ch -5.8	1000101	45h -9.9	1101110	6Eh -14
		0011101	1Dh -5.9	1000110	46h -10	1101111	6Fh -14.1
		0011110	1Eh -6	1000111	47h -10.1	1110000	70h -14.2
		0011111	1Fh -6.1	1001000	48h -10.2	1110001	71h -14.3
		0100000	20h -6.2	1001001	49h -10.3	1110010	72h -14.4
		0100001	21h -6.3	1001010	4Ah -10.4	1110011	73h -14.5
		0100010	22h -6.4	1001011	4Bh -10.5	1110100	74h -14.6
		0100011	23h -6.5	1001100	4Ch -10.6	1110101	75h -14.7
		0100100	24h -6.6	1001101	4Dh -10.7	1110110	76h -14.8
		0100101	25h -6.7	1001110	4Eh -10.8	1110111	77h -14.9
		0100110	26h -6.8	1001111	4Fh -10.9	1111000	78h -15
		0100111	27h -6.9	1010000	50h -11	other	-15
		0101000	28h -7	1010001	51h -7.1		

Notes:

1. VSP_0/VSN_0 voltage output is ± 15 V fixed value.
2. When switching Mode0 or Mode1, the voltage output is:
 Mode0: VSP_0(+15) / VSN_0 (-15) / VSPL_0 (+3~+15)
 Mode1: VSP_1(+3 ~ +15) / VSN_1(-3 ~ -15) / VSPL_1(+3 ~ +15)

	Mode0	Mode1
VSP	VSP_0(+15)	VSP_1(+3~+15)
VSN	VSN_0(-15)	VSN_1(-3~-15)
VSPL	VSPL_0(+3~+15)	VSPL_1(+3~+15)

3. If gate voltage is set to ± 15 v, ± 10 v, IC will auto correct source voltage as follows
 I. VGP- VSP_0 / VSPL_0 / VSP_1 / VSPL_1 ≥ 2 v
 II. VGN- VSN_0 / VSN_1 ≥ -2 v
 For example:

	symbol	Voltage setting	Real Voltage
Voltage	VGP	+10v	+10v
	VGN	-10v	-10v
	VSP_0	+15v	+8v
	VSN_0	-15v	-8v
	VSP_1	+5v	+5v
	VSN_1	-5v	-5v
	VSPL	+15v	+8v
	VCOMH	+15v+(-2v)	+8v +(-2v)
	VCOML	-15v+(-2v)	-8v +(-2v)
	VCOMDC	-2v	-2v

Restriction

R02H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
POF	W	0	0	0	0	0	0	0	1	0	02H
1 st Parameter	W	0	-	-	-	-	-	-	-	-	00

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as : - After power off command, driver will power off base on power off sequence. - After power off command, BUSY_N signal will drop from high to low. When finish the power off sequence, BUSY_N signal will rise from low to high. - Power off command will turn off charge pump, T-con, source driver, gate driver, VCOM, temperature sensor, but register and SRAM data will keep until VDD off. - SD output and VCOM will base on previous condition. It may have two conditions: 0v or floating.
Restriction	This command only active when BUSY_N = "1".

R04H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
PON	W	0	0	0	0	0	0	1	0	0	04H

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as : - After power on command, driver will power on base on power on sequence. - After power on command, BUSY_N signal will drop from high to low. When finishing the power on sequence (base on PWR command), BUSY_N signal will rise from low to high.
Restriction	This command only active when BUSY_N = "1".

R06H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
BTST	W	0	0	0	0	0	0	1	1	0	06H
1 st Parameter	W	1	-	-	-	-	PHB_SFT [1:0]		PHA_SFT [1:0]		00h
2 nd Parameter	W	1	-	-	PHA_ON [5:0]						02h
3 rd Parameter	W	1	-	-	PHA_OFF [5:0]						07h
4 th Parameter	W	1	-	-	PHB_ON [5:0]						02h
5 th Parameter	W	1	-	-	PHB_OFF [5:0]						07h
6 th Parameter	W	1	-	-	PHC_ON [5:0]						02h
7 th Parameter	W	1	-	-	PHC_OFF [5:0]						07h

Description	-The command define as follows: Boost Current mode and Constant On Time mode setting by JD CMD 1 st Parameter:					
	Bit	Name	Description			
	1-0	PHA_SFT	Soft start period of phase A: 00: 10mS (default) 01: 20mS 10: 30mS 11: 40mS			
Driving strength of PHA_ON & PHB_ON & PHC_ON	3-2	PHB_SFT	Soft start period of phase B: 00: 10mS (default) 01: 20mS 10: 30mS 11: 40mS			
			Bit[5:0]	Description	Bit[5:0]	Description
			000000	strength1	010110	strength23
			000001	strength2	010111	strength24
			000010	strength3	011000	strength25
			000011	strength4	011001	strength26
			000100	strength5	011010	strength27
			000101	strength6	011011	strength28
			000110	strength7	011100	strength29
			000111	strength8	011101	strength30
			001000	strength9	011110	strength31
			001001	strength10	011111	strength32
			001010	strength11	100000	strength33
			001011	strength12	100001	strength34
			001100	strength13	100010	strength35
			001101	strength14	100011	strength36
			001110	strength15	100100	strength37
			001111	strength16	100101	strength38
			010000	strength17	100110	strength39
			010001	strength18	100111	strength40
			010010	strength19	101000	strength41
			010011	strength20	101001	strength42
			010100	strength21	101010	strength43
			010101	strength22	101011	strength44

Description	Bit[5:0]	Description	Bit[5:0]	Description	Bit[5:0]	Description
Minimum OFF time setting of PHA_OFF & PHB_OFF & PHC_OFF	000000	Period1	010110	Period23	101100	Period45
	000001	Period2	010111	Period24	101101	Period46
	000010	Period3	011000	Period25	101110	Period47
	000011	Period4	011001	Period26	101111	Period48
	000100	Period5	011010	Period27	110000	Period49
	000101	Period6	011011	Period28	110001	Period50
	000110	Period7	011100	Period29	110010	Period51
	000111	Period8	011101	Period30	110011	Period52
	001000	Period9	011110	Period31	110100	Period53
	001001	Period10	011111	Period32	110101	Period54
	001010	Period11	100000	Period33	110110	Period55
	001011	Period12	100001	Period34	110111	Period56
	001100	Period13	100010	Period35	111000	Period57
	001101	Period14	100011	Period36	111001	Period58
	001110	Period15	100100	Period37	111010	Period59
	001111	Period16	100101	Period38	111011	Period60
	010000	Period17	100110	Period39	111100	Period61
	010001	Period18	100111	Period40	111101	Period62
	010010	Period19	101000	Period41	111110	Period63
	010011	Period20	101001	Period42	111111	Period64
	010100	Period21	101010	Period43		
	010101	Period22	101011	Period44		
Restriction						

R07H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
DSLP	W	0	0	0	0	0	0	1	1	1	07H
1 st Parameter	W	1	1	0	1	0	0	1	0	1	A5h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	The command define as follows: After this command is transmitted, the chip would enter the deep-sleep mode to save power. The deep sleep mode would return to standby by hardware reset. The only one parameter is a check code, the command would be excited if check code = 0xA5.										
Restriction	This command only active when BUSY_N = "1".										

R10H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
DTM_master	W	0	0	0	0	1	0	0	0	0	10H
1 st Parameter	W	1	Pixel1		Pixel2		Pixel3		Pixel4		00h
:	W	1	:		:		:		:		00h
M th Parameter	W	1	Pixel(n-3)		Pixel(n-2)		Pixel(n-1)		Pixel(n)		00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	The command define as follows: The register is indicates that user start to transmit data, then write to SRAM. While data transmission complete, user must send command 12H. Then chip will start to send data/VCOM for panel.										
-------------	--	--	--	--	--	--	--	--	--	--	--

	Pixel [1~n][1:0]: 2-bit/pixel				
	Image Data	DDX=1(default)		DDX=0	
	Pixel[1:0]	Gray level select	IP output LUT select	Gray level select	IP output LUT select
	00b	Gray0	ogray00	Gray3	ogray03
	01b	Gray1	ogray01	Gray2	ogray02
	10b	Gray2	ogray02	Gray1	ogray01
	11b	Gray3	ogray03	Gray0	ogray00
Data mapping example: When DDX=1, Pixel[1:0]=01 -> Gray level select=Gray1, follow LUT data output from IP output port "ogray01". When DDX=0, Pixel[1:0]=11 -> Gray level select=Gray0, follow LUT data output from IP output port "ogray00".					
Restriction					

R11H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
DSP	W	0	0	0	0	1	0	0	0	1	11H
1 st Parameter	R	1	Data_flag	-	-	-	-	-	-	-	-

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as :					
	■ While finished the data transmitting, user must send this command to driver and read Data_flag information.					
	1 st Parameter:					
	<table><tr><th>Bit</th><th>Name</th><th>Description</th></tr><tr><td>7</td><td>Data_flag</td><td>0: Driver didn't receive all the data. 1: Driver has already received all of the one frame data.</td></tr></table>	Bit	Name	Description	7	Data_flag
Bit	Name	Description				
7	Data_flag	0: Driver didn't receive all the data. 1: Driver has already received all of the one frame data.				
After "Data Start" (10h) or "Data Stop" (11h) commands and when data_flag=1, BUSY_N signal will become "0" and the refreshing of panel starts.						
Restriction	This command only actives when BUSY_N = "1".					

R12H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
DRF	W	0	0	0	0	1	0	0	1	0	12H
1 st Parameter	W	1	-	-	-	-	-	-	-	-	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as : R12h=0x00 While users send this command, driver will refresh display (data/VCOM) base on SRAM data and LUT. After display refresh command, BUSY_N signal will become "0"										
Restriction	This command only actives when BUSY_N = "1"										

R17H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
Auto Sequence	W	0	0	0	0	1	0	1	1	1	17H
1 st Parameter	W	1	Code[7]	Code[6]	Code[5]	Code[4]	Code[3]	Code[2]	Code[1]	Code[0]	A5h

Description	The command can enable the internal sequence to execute several commands continuously. The successive execution can minimize idle time to avoid unnecessary power consumption and reduce the complexity of host's control procedure. The sequence contains several operations, including PON, DRF, POF, DSLP. AUTO (0x17) + Code(0xA5) = (PON→DRF→POF) AUTO (0x17) + Code(0xA7) = (PON→DRF→POF→DSLP)										
Restriction	This command only actives when BUSY_N = "1".										

R30H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
PLL	W	0	0	0	1	1	0	0	0	0	30H
1 st Parameter	W	1	-	-	-	-	Dyna	FR[2]	FR[1]	FR[0]	02h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as: The command controls the PLL clock frequency. The PLL structure must support the following frame rates: <table border="1"> <thead> <tr> <th>bit3</th><th>Dynamic frame rate</th></tr> </thead> <tbody> <tr> <td>0</td><td>Disable(default)</td></tr> <tr> <td>1</td><td>Enable</td></tr> </tbody> </table> Note: Dynamic frame rate 0: Frame rate will being defined in R30h. 1: Frame rate will being defined by R20h(LUT). <table border="1"> <thead> <tr> <th>FR[2:0]</th><th>Frame rate</th></tr> </thead> <tbody> <tr> <td>000</td><td>12.5 Hz</td></tr> <tr> <td>001</td><td>25 Hz</td></tr> <tr> <td>010</td><td>50 Hz(default)</td></tr> <tr> <td>011</td><td>65 Hz</td></tr> <tr> <td>100</td><td>75 Hz</td></tr> <tr> <td>101</td><td>85 Hz</td></tr> <tr> <td>110</td><td>100 Hz</td></tr> <tr> <td>111</td><td>120 Hz</td></tr> </tbody> </table>	bit3	Dynamic frame rate	0	Disable(default)	1	Enable	FR[2:0]	Frame rate	000	12.5 Hz	001	25 Hz	010	50 Hz(default)	011	65 Hz	100	75 Hz	101	85 Hz	110	100 Hz	111	120 Hz
bit3	Dynamic frame rate																								
0	Disable(default)																								
1	Enable																								
FR[2:0]	Frame rate																								
000	12.5 Hz																								
001	25 Hz																								
010	50 Hz(default)																								
011	65 Hz																								
100	75 Hz																								
101	85 Hz																								
110	100 Hz																								
111	120 Hz																								
remark	-Horizontal -Vertical																								
Restriction																									

R40H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
TSC	W	0	0	1	0	0	0	0	0	0	40H
1 st Parameter	R	1	D10/TS[7]	D9/TS[6]	D8/TS[5]	D7/TS[4]	D6/TS[3]	D5/TS[2]	D4/TS[1]	D3/TS[0]	-
2 nd Parameter	R	1	D2/TS[9]	D1/TS[8]	D0	-	-	-	-	-	-

NOTE: "-" Don't care, can be set to VDD or GND level

Description

-The command define as follows:

This command indicates the temperature value.

If R41H(TSE) bit7 set to 0, this command reads internal temperature sensor value.

If R41H(TSE) bit7 set to 1, this command reads external (LM75) temperature sensor value

TS[7:0]/D[10:3]	T (°C)	TS[7:0]/D[10:3]	T (°C)	TS[7:0]/D[10:3]	T (°C)
11100111	-25	00000000	0	00011001	25
11101000	-24	00000001	1	00011010	26

11101001	-23	00000010	2	00011011	27
11101010	-22	00000011	3	00011100	28
11101011	-21	00000100	4	00011101	29
11101100	-20	00000101	5	00011110	30
11101101	-19	00000110	6	00011111	31
11101110	-18	00000111	7	00100000	32
11101111	-17	00001000	8	00100001	33
11110000	-16	00001001	9	00100010	34
11110001	-15	00001010	10	00100011	35
11110010	-14	00001011	11	00100100	36
11110011	-13	00001100	12	00100101	37
11110100	-12	00001101	13	00100110	38
11110101	-11	00001110	14	00100111	39
11110110	-10	00001111	15	00101000	40
11110111	-9	00010000	16	00101001	41
11111000	-8	00010001	17	00101010	42
11111001	-7	00010010	18	00101011	43
11111010	-6	00010011	19	00101100	44
11111011	-5	00010100	20	00101101	45
11111100	-4	00010101	21	00101110	46
11111101	-3	00010110	22	00101111	47
11111110	-2	00010111	23	00110000	48
11111111	-1	00011000	24	00110001	49

TS[9:8]	T (°C)
00	+0
01	+0.25
10	+0.5
11	+0.75

Restriction	This command only actives when BUSY_N = "1".
-------------	--

R41H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
TSE	W	0	0	1	0	0	0	0	0	1	41H
1 st Parameter	W	1	TSE	-	-	TO[4]	TO[3]	TO[2]	TO[1]	TO[0]	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as: This command indicates the driver IC temperature sensor enable and calibration function.													
	Reserve one temperature offset TO[3:0] for calibration													
	1. TO[3]: mean '+' or '-', while 0 is '+' ; 1 is '-'													
	2. TO[2:0]: mean temperature offset value													
	<table><tr><th>Bit</th><th>Name</th><th>Description</th></tr><tr><td>3-0</td><td>TO[3:0]</td><td>Temperature level: 0000: +0°C (default) 0001: +0.5°C 0010: +1°C 0011: +1.5°C 0100: +2°C 0101: +2.5°C 0110: +3°C 0111: +3.5°C 1000: -4°C 1001: -3.5°C 1010: -3°C 1011: -2.5°C 1100: -2°C 1101: -1.5°C 1110: -1°C 1111: -0.5°C</td></tr><tr><td>4</td><td>TO[4]</td><td>0: +0.0°C (default) 1: +0.25°C</td></tr><tr><td>7</td><td>TSE</td><td>Internal temperature sensor enable 0: Internal temperature sensor enable.(default) 1: Internal temperature sensor disable, using external temperature sensor.</td></tr></table>			Bit	Name	Description	3-0	TO[3:0]	Temperature level: 0000: +0°C (default) 0001: +0.5°C 0010: +1°C 0011: +1.5°C 0100: +2°C 0101: +2.5°C 0110: +3°C 0111: +3.5°C 1000: -4°C 1001: -3.5°C 1010: -3°C 1011: -2.5°C 1100: -2°C 1101: -1.5°C 1110: -1°C 1111: -0.5°C	4	TO[4]	0: +0.0°C (default) 1: +0.25°C	7	TSE
Bit	Name	Description												
3-0	TO[3:0]	Temperature level: 0000: +0°C (default) 0001: +0.5°C 0010: +1°C 0011: +1.5°C 0100: +2°C 0101: +2.5°C 0110: +3°C 0111: +3.5°C 1000: -4°C 1001: -3.5°C 1010: -3°C 1011: -2.5°C 1100: -2°C 1101: -1.5°C 1110: -1°C 1111: -0.5°C												
4	TO[4]	0: +0.0°C (default) 1: +0.25°C												
7	TSE	Internal temperature sensor enable 0: Internal temperature sensor enable.(default) 1: Internal temperature sensor disable, using external temperature sensor.												
Restriction	This command only actives after R04H(PON)													


R42H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
TSW	W	0	0	1	0	0	0	0	1	0	42H
1 st Parameter	W	1	WATTR[7]	WATTR[6]	WATTR[5]	WATTR[4]	WATTR[3]	WATTR[2]	WATTR[1]	WATTR[0]	00h
2 nd Parameter	W	1	WMSB[7]	WMSB[6]	WMSB[5]	WMSB[4]	WMSB[3]	WMSB[2]	WMSB[1]	WMSB[0]	00h
3 rd Parameter	W	1	WLSB[7]	WLSB[6]	WLSB[5]	WLSB[4]	WLSB[3]	WLSB[2]	WLSB[1]	WLSB[0]	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as:		
	This command writes the temperature.		
	1 st Parameter:		
	Bit	Name	Description
	2-0	WATTR[2:0]	Pointer setting
	5-3	WATTR[5:3]	User-defined address bits (A2, A1, A0)
	7-6	WATTR[7:6]	I2C Write Byte Number 00: 1 byte (head byte only) 01: 2 bytes (head byte + pointer) 10: 3 bytes (head byte + pointer + 1 st parameter) 11: 4 bytes (head byte + pointer + 1 st parameter + 2 nd parameter)
	2 nd Parameter:		
	Bit	Name	Description
	7-0	WMSB[7:0]	MSByte of write-data to external temperature sensor
3 rd Parameter:	Bit	Name	Description
	7-0	WLSB[7:0]	LSByte of write-data to external temperature sensor
	Restriction		
This command only actives after R04H(PON)			

R43H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
TSR	W	0	0	1	0	0	0	0	1	1	43H
1 st Parameter	R	1	RMSB[7]	RMSB[6]	RMSB[5]	RMSB[4]	RMSB[3]	RMSB[2]	RMSB[1]	RMSB[0]	-
2 nd Parameter	R	1	RLSB[7]	RLSB[6]	RLSB[5]	RLSB[4]	RLSB[3]	RLSB[2]	RLSB[1]	RLSB[0]	-

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as:								
	This command reads the temperature sensed by the temperature sensor.								
	1 st Parameter:								
	<table><tr><th>Bit</th><th>Name</th><th>Description</th></tr><tr><td>7-0</td><td>RMSB[7:0]</td><td>MSByte of read-data from external temperature sensor</td></tr></table>	Bit	Name	Description	7-0	RMSB[7:0]	MSByte of read-data from external temperature sensor		
	Bit	Name	Description						
7-0	RMSB[7:0]	MSByte of read-data from external temperature sensor							
2 nd Parameter:									
<table><tr><th>Bit</th><th>Name</th><th>Description</th></tr><tr><td>7-0</td><td>RLSB[7:0]</td><td>LSByte of write-data from external temperature sensor</td></tr></table>	Bit	Name	Description	7-0	RLSB[7:0]	LSByte of write-data from external temperature sensor			
Bit	Name	Description							
7-0	RLSB[7:0]	LSByte of write-data from external temperature sensor							
									
Restriction	This command only actives after R04H(PON)								

R50H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
CDI	W	0	0	1	0	1	0	0	0	0	50H
1 st Parameter	W	1	VBD[2]	VBD[1]	VBD [0]	DDX	CDI[3]	CDI[2]	CDI[1]	CDI[0]	97h

NOTE: "-" Don't care, can be set to VDD or GND level

Description

-The command defines as:
This command can set 2 kinds of parameters, 1.VCOM to data output interval(CDI)
:
CDI[3:0]: This command indicates the interval of VCOM and data output. When setting the vertical back porch, the total blanking will be keep (55hsync).


Bit	Name	Description
3-0	CDI[3:0]	Vcom and data interval 0000: 17 hsync 0001:16 hsync 0010:15 hsync 0011:14 hsync 0100:13 hsync 0101:12 hsync 0110:11 hsync 0111:10 hsync(default) 1000:9 hsync 1001:8 hsync 1010:7 hsync 1011:6 hsync 1100:5 hsync 1101:4 hsync 1110:3 hsync 1111:2 hsync

The diagram illustrates the timing of various signals during a video frame. The signals shown are:

- Internal vsync**: A square wave signal.
- Internal hsync**: A series of horizontal sync pulses.
- Internal de**: A signal that transitions from high to low at the start of a frame.
- VCOM**: A signal that transitions from low to high at the start of a frame and remains high until the start of the next frame.
- Source data Output**: A signal that transitions from low to high at the start of a frame and remains high until the start of the next frame.

Key timing points and intervals are marked:

- VCOM need to be ready before source data output**: A purple text label indicating the required setup time for VCOM before data output begins.
- VCOM output location (fixed)**: A blue text label indicating the fixed position of the VCOM output.
- Frame N VCOM**: The duration of the VCOM signal for Frame N.
- Frame N data**: The duration of the source data output for Frame N.
- Frame N+1 VCOM**: The duration of the VCOM signal for Frame N+1.
- CDI setting**: A red arrow indicating the interval between the start of the VCOM signal and the start of the source data output.
- 55 hsync-CDI setting (fixed)**: A dashed line marking the end of the CDI setting interval, which is fixed to 55 hsync.



VBD[2:0]: Border data selection. (from LUT output by IP port border_w[1:0])			
This register will make boarder pin output being mapped to a certain gray scale.			
Bit 4	Bit7-5	Description	IP setting for Border LUT select
DDX	VBD[2:0]	Gray level	
0	000	Floating	N/A
	001	Gray3	border_buf=011
	010	Gray2	border_buf=010
	011	Gray1	border_buf=001
	100	Gray0	border_buf=000
1 (default)	000	Gray0	border_buf=000
	001	Gray1	border_buf=001
	010	Gray2	border_buf=010
	011	Gray3	border_buf=011
	100	Floating	N/A

Border output voltage level: The level selection is based on mapping LUT data.

Ex: Gray 1 waveform is mapping to 15V, without VCOM offset, the real output on Boarder pin shall be 15V.

Boarder output will follow FOPT definition being defined in R00h.

R51H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
LPD	W	0	0	1	0	1	0	0	0	1	51H
1 st Parameter	R	1	-	-	-	-	-	-	-	LPD	--

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as: This command indicates the input power condition. Host can read this data to understand the battery's condition. When LPD="1", system input power is normal. When LPD="0", system input power is lower (VDD<2.5v, which could be select in RE4H (LVSEL)). 1st Parameter: <table border="1"> <tr> <th>Bit 0</th><th>LPD</th></tr> <tr> <td>0</td><td>Low power input.</td></tr> <tr> <td>1</td><td>Normal status.</td></tr> </table>	Bit 0	LPD	0	Low power input.	1	Normal status.
Bit 0	LPD						
0	Low power input.						
1	Normal status.						
Restriction	This command only actives when BUSY_N = "1".						

R61H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
TRES	W	0	0	1	1	0	0	0	0	1	61H
1 st Parameter	W	1	-	-	-	-	-	-	HRES(9)	HRES(8)	00h
2 nd Parameter	W	1	HRES(7)	HRES(6)	HRES(5)	HRES(4)	HRES(3)	HRES(2)	0	0	00h
3 th Parameter	W	1	-	-	-	-	-	-	VRES(9)	VRES(8)	00h
4 th Parameter	W	1	VRES(7)	VRES(6)	VRES(5)	VRES(4)	VRES(3)	VRES(2)	VRES(1)	VRES(0)	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command define as follows: When using register: Horizontal display resolution(source) = HRES Vertical display resolution(gate) = VRES Note: No matter HRES[9:8],HRES[1:0],VRES[9:8] value being filled, it's always be 00b. Channel disable calculation: GD : First G active = G0; LAST active GD= first active +VRES[9:0] -1 SD : First active channel: =S0 ; LAST active SD= first active +HRES[9:2]*4-1 EX :128x250 GD: First G active = G0 LAST active GD= 0+250-1= 249; (G249) SD : First active channel: =S0 LAST active SD=0+32*4-1=127; (S127)
Restriction	Horizontal resolution should be 4-multiple.

R65H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
GSST	W	0	0	1	1	0	0	1	0	1	65H
1 st Parameter	W	1	-	-	-	-	-	-	S_start[9]	S_start[8]	00h
2 nd Parameter	W	1	S_start[7]	S_start[6]	S_start[5]	S_start[4]	S_start[3]	S_start[2]	0	0	00h
3 rd Parameter	W	1	-	-	-	-	-	-	G_start[9]	G_start[8]	00h
4 th Parameter	W	1	G_start[7]	G_start[6]	G_start[5]	G_start[4]	G_start[3]	G_start[2]	G_start[1]	G_start[0]	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command define as follows: Note: No matter S_start[9:8], S_start [1:0], G_start [9:8] value being filled, it's always be 00b. 1.S_Start [8:0] describe which source output line is the first date line 2.G_Start[8:0] describe which gate line is the first scan line
Restriction	S_Start should be the multiple of 4

R70H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
REV	W	0	0	1	1	1	0	0	0	0	70H
1 st Parameter	R	1	0	0	0	0	1	0	0	1	09h
2 nd Parameter	R	1	0	0	0	0	0	0	1	0	02h
3 rd Parameter	R	1	0	0	0	0	0	0	0	1	01h


NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as: 1 st & 2 nd & 3 rd Parameter: <table border="1" data-bbox="427 846 970 936"> <thead> <tr> <th>Bit</th><th>Description</th></tr> </thead> <tbody> <tr> <td>7-0</td><td>CHIP_REV</td></tr> </tbody> </table>	Bit	Description	7-0	CHIP_REV
Bit	Description				
7-0	CHIP_REV				
Restriction					

R80H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
AMV	W	0	1	0	0	0	0	0	0	0	80H
1 st Parameter	W	1	P[1]	P[0]	AMVT[1]	AMVT[0]	XON	AMVS	AMV	AMVE	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as: This command indicates the IC status. Host can read this data to understand the IC status.		
	1 st Parameter:		
	Bit	Name	Description
	0	AMVE	AMVE: Auto Measure Vcom Setting 0: Auto measure VCOM disable (default) 1: Auto measure VCOM enable
	1	AMV	AMV: Analog signal 0: Get Vcom value from R81h(default) 1: Get Vcom value in analog signal
	2	AMVS	AMVS: setting for Source output of AMV 0: Source output 0V during Auto Measure VCOM period. (default) 1: Source output VSPL_0 during Auto Measure VCOM period.
	3	XON	XON: setting for all Gate ON of AMV 0: Gate normally scan during Auto Measure VCOM period. (default) 1: All Gate ON during Auto Measure VCOM period.
	5-4	AMVT[1:0]	The sensing time of VCOM detection 00: 5s (default) 01: 10s 10: 15s 11: 20s
7-6	P[1:0]	The sensing points of sampling time 00: 2 (default) 01: 4 10: 8 11: 16 Sampling time = the last quarter of sensing time (T) VCOM = average of N points. N=2,4,8,16	



R81H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
VV	W	0	1	0	0	0	0	0	0	1	81H
1 st Parameter	R	1	-	VV[6]	VV[5]	VV[4]	VV[3]	VV[2]	VV[1]	VV[0]	--

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as: This command could get the VCOM value 1st Parameter: <table> <tr> <th>Bit</th><th>Name</th><th colspan="10">Description</th></tr> <tr> <td rowspan="30">6-0</td><td rowspan="30">VV[6:0]</td><td colspan="10">VCOM value</td></tr> <tr> <td>VV [6:0]</td><td>Voltage(V)</td><td>VV [6:0]</td><td>Voltage(V)</td><td>VV [6:0]</td><td>Voltage(V)</td><td>VV [6:0]</td><td>Voltage(V)</td><td>VV [6:0]</td><td>Voltage(V)</td></tr> <tr><td>0000000</td><td>00h</td><td>0</td><td>0011100</td><td>1Ch</td><td>-1.4</td><td>0111000</td><td>38h</td><td>-2.8</td><td></td></tr> <tr><td>0000001</td><td>01h</td><td>-0.05</td><td>0011101</td><td>1Dh</td><td>-1.45</td><td>0111001</td><td>39h</td><td>-2.85</td><td></td></tr> <tr><td>0000010</td><td>02h</td><td>-0.1</td><td>0011110</td><td>1Eh</td><td>-1.5</td><td>0111010</td><td>3Ah</td><td>-2.9</td><td></td></tr> <tr><td>0000011</td><td>03h</td><td>-0.15</td><td>0011111</td><td>1Fh</td><td>-1.55</td><td>0111011</td><td>3Bh</td><td>-2.95</td><td></td></tr> <tr><td>0000100</td><td>04h</td><td>-0.2</td><td>0100000</td><td>20h</td><td>-1.6</td><td>0111100</td><td>3Ch</td><td>-3</td><td></td></tr> <tr><td>0000101</td><td>05h</td><td>-0.25</td><td>0100001</td><td>21h</td><td>-1.65</td><td>0111101</td><td>3Dh</td><td>-3.05</td><td></td></tr> <tr><td>0000110</td><td>06h</td><td>-0.3</td><td>0100010</td><td>22h</td><td>-1.7</td><td>0111110</td><td>3Eh</td><td>-3.1</td><td></td></tr> <tr><td>0000111</td><td>07h</td><td>-0.35</td><td>0100011</td><td>23h</td><td>-1.75</td><td>0111111</td><td>3Fh</td><td>-3.15</td><td></td></tr> <tr><td>0001000</td><td>08h</td><td>-0.4</td><td>0100100</td><td>24h</td><td>-1.8</td><td>1000000</td><td>40h</td><td>-3.2</td><td></td></tr> <tr><td>0001001</td><td>09h</td><td>-0.45</td><td>0100101</td><td>25h</td><td>-1.85</td><td>1000001</td><td>41h</td><td>-3.25</td><td></td></tr> <tr><td>0001010</td><td>0Ah</td><td>-0.5</td><td>0100110</td><td>26h</td><td>-1.9</td><td>1000010</td><td>42h</td><td>-3.3</td><td></td></tr> <tr><td>0001011</td><td>0Bh</td><td>-0.55</td><td>0100111</td><td>27h</td><td>-1.95</td><td>1000011</td><td>43h</td><td>-3.35</td><td></td></tr> <tr><td>0001100</td><td>0Ch</td><td>-0.6</td><td>0101000</td><td>28h</td><td>-2</td><td>1000100</td><td>44h</td><td>-3.4</td><td></td></tr> <tr><td>0001101</td><td>0Dh</td><td>-0.65</td><td>0101001</td><td>29h</td><td>-2.05</td><td>1000101</td><td>45h</td><td>-3.45</td><td></td></tr> <tr><td>0001110</td><td>0Eh</td><td>-0.7</td><td>0101010</td><td>2Ah</td><td>-2.1</td><td>1000110</td><td>46h</td><td>-3.5</td><td></td></tr> <tr><td>0001111</td><td>0Fh</td><td>-0.75</td><td>0101011</td><td>2Bh</td><td>-2.15</td><td>1000111</td><td>47h</td><td>-3.55</td><td></td></tr> <tr><td>0010000</td><td>10h</td><td>-0.8</td><td>0101100</td><td>2Ch</td><td>-2.2</td><td>1001000</td><td>48h</td><td>-3.6</td><td></td></tr> <tr><td>0010001</td><td>11h</td><td>-0.85</td><td>0101101</td><td>2Dh</td><td>-2.25</td><td>1001001</td><td>49h</td><td>-3.65</td><td></td></tr> <tr><td>0010010</td><td>12h</td><td>-0.9</td><td>0101110</td><td>2Eh</td><td>-2.3</td><td>1001010</td><td>4Ah</td><td>-3.7</td><td></td></tr> <tr><td>0010011</td><td>13h</td><td>-0.95</td><td>0101111</td><td>2Fh</td><td>-2.35</td><td>1001011</td><td>4Bh</td><td>-3.75</td><td></td></tr> <tr><td>0010100</td><td>14h</td><td>-1</td><td>0110000</td><td>30h</td><td>-2.4</td><td>1001100</td><td>4Ch</td><td>-3.8</td><td></td></tr> <tr><td>0010101</td><td>15h</td><td>-1.05</td><td>0110001</td><td>31h</td><td>-2.45</td><td>1001101</td><td>4Dh</td><td>-3.85</td><td></td></tr> <tr><td>0010110</td><td>16h</td><td>-1.1</td><td>0110010</td><td>32h</td><td>-2.5</td><td>1001110</td><td>4Eh</td><td>-3.9</td><td></td></tr> <tr><td>0010111</td><td>17h</td><td>-1.15</td><td>0110011</td><td>33h</td><td>-2.55</td><td>1001111</td><td>4Fh</td><td>-3.95</td><td></td></tr> <tr><td>0011000</td><td>18h</td><td>-1.2</td><td>0110100</td><td>34h</td><td>-2.6</td><td>1010000</td><td>50h</td><td>-4</td><td></td></tr> <tr><td>0011001</td><td>19h</td><td>-1.25</td><td>0110101</td><td>35h</td><td>-2.65</td><td>other</td><td></td><td>-4</td><td></td></tr> <tr><td>0011010</td><td>1Ah</td><td>-1.3</td><td>0110110</td><td>36h</td><td>-2.7</td><td></td><td></td><td></td><td></td></tr> <tr><td>0011011</td><td>1Bh</td><td>-1.35</td><td>0110111</td><td>37h</td><td>-2.75</td><td></td><td></td><td></td><td></td></tr> </table>											Bit	Name	Description										6-0	VV[6:0]	VCOM value										VV [6:0]	Voltage(V)	VV [6:0]	Voltage(V)	VV [6:0]	Voltage(V)	VV [6:0]	Voltage(V)	VV [6:0]	Voltage(V)	0000000	00h	0	0011100	1Ch	-1.4	0111000	38h	-2.8		0000001	01h	-0.05	0011101	1Dh	-1.45	0111001	39h	-2.85		0000010	02h	-0.1	0011110	1Eh	-1.5	0111010	3Ah	-2.9		0000011	03h	-0.15	0011111	1Fh	-1.55	0111011	3Bh	-2.95		0000100	04h	-0.2	0100000	20h	-1.6	0111100	3Ch	-3		0000101	05h	-0.25	0100001	21h	-1.65	0111101	3Dh	-3.05		0000110	06h	-0.3	0100010	22h	-1.7	0111110	3Eh	-3.1		0000111	07h	-0.35	0100011	23h	-1.75	0111111	3Fh	-3.15		0001000	08h	-0.4	0100100	24h	-1.8	1000000	40h	-3.2		0001001	09h	-0.45	0100101	25h	-1.85	1000001	41h	-3.25		0001010	0Ah	-0.5	0100110	26h	-1.9	1000010	42h	-3.3		0001011	0Bh	-0.55	0100111	27h	-1.95	1000011	43h	-3.35		0001100	0Ch	-0.6	0101000	28h	-2	1000100	44h	-3.4		0001101	0Dh	-0.65	0101001	29h	-2.05	1000101	45h	-3.45		0001110	0Eh	-0.7	0101010	2Ah	-2.1	1000110	46h	-3.5		0001111	0Fh	-0.75	0101011	2Bh	-2.15	1000111	47h	-3.55		0010000	10h	-0.8	0101100	2Ch	-2.2	1001000	48h	-3.6		0010001	11h	-0.85	0101101	2Dh	-2.25	1001001	49h	-3.65		0010010	12h	-0.9	0101110	2Eh	-2.3	1001010	4Ah	-3.7		0010011	13h	-0.95	0101111	2Fh	-2.35	1001011	4Bh	-3.75		0010100	14h	-1	0110000	30h	-2.4	1001100	4Ch	-3.8		0010101	15h	-1.05	0110001	31h	-2.45	1001101	4Dh	-3.85		0010110	16h	-1.1	0110010	32h	-2.5	1001110	4Eh	-3.9		0010111	17h	-1.15	0110011	33h	-2.55	1001111	4Fh	-3.95		0011000	18h	-1.2	0110100	34h	-2.6	1010000	50h	-4		0011001	19h	-1.25	0110101	35h	-2.65	other		-4		0011010	1Ah	-1.3	0110110	36h	-2.7					0011011	1Bh	-1.35	0110111	37h	-2.75				
Bit	Name	Description																																																																																																																																																																																																																																																																																																																																			
6-0	VV[6:0]	VCOM value																																																																																																																																																																																																																																																																																																																																			
		VV [6:0]	Voltage(V)	VV [6:0]	Voltage(V)	VV [6:0]	Voltage(V)	VV [6:0]	Voltage(V)	VV [6:0]	Voltage(V)																																																																																																																																																																																																																																																																																																																										
		0000000	00h	0	0011100	1Ch	-1.4	0111000	38h	-2.8																																																																																																																																																																																																																																																																																																																											
		0000001	01h	-0.05	0011101	1Dh	-1.45	0111001	39h	-2.85																																																																																																																																																																																																																																																																																																																											
		0000010	02h	-0.1	0011110	1Eh	-1.5	0111010	3Ah	-2.9																																																																																																																																																																																																																																																																																																																											
		0000011	03h	-0.15	0011111	1Fh	-1.55	0111011	3Bh	-2.95																																																																																																																																																																																																																																																																																																																											
		0000100	04h	-0.2	0100000	20h	-1.6	0111100	3Ch	-3																																																																																																																																																																																																																																																																																																																											
		0000101	05h	-0.25	0100001	21h	-1.65	0111101	3Dh	-3.05																																																																																																																																																																																																																																																																																																																											
		0000110	06h	-0.3	0100010	22h	-1.7	0111110	3Eh	-3.1																																																																																																																																																																																																																																																																																																																											
		0000111	07h	-0.35	0100011	23h	-1.75	0111111	3Fh	-3.15																																																																																																																																																																																																																																																																																																																											
		0001000	08h	-0.4	0100100	24h	-1.8	1000000	40h	-3.2																																																																																																																																																																																																																																																																																																																											
		0001001	09h	-0.45	0100101	25h	-1.85	1000001	41h	-3.25																																																																																																																																																																																																																																																																																																																											
		0001010	0Ah	-0.5	0100110	26h	-1.9	1000010	42h	-3.3																																																																																																																																																																																																																																																																																																																											
		0001011	0Bh	-0.55	0100111	27h	-1.95	1000011	43h	-3.35																																																																																																																																																																																																																																																																																																																											
		0001100	0Ch	-0.6	0101000	28h	-2	1000100	44h	-3.4																																																																																																																																																																																																																																																																																																																											
		0001101	0Dh	-0.65	0101001	29h	-2.05	1000101	45h	-3.45																																																																																																																																																																																																																																																																																																																											
		0001110	0Eh	-0.7	0101010	2Ah	-2.1	1000110	46h	-3.5																																																																																																																																																																																																																																																																																																																											
		0001111	0Fh	-0.75	0101011	2Bh	-2.15	1000111	47h	-3.55																																																																																																																																																																																																																																																																																																																											
		0010000	10h	-0.8	0101100	2Ch	-2.2	1001000	48h	-3.6																																																																																																																																																																																																																																																																																																																											
		0010001	11h	-0.85	0101101	2Dh	-2.25	1001001	49h	-3.65																																																																																																																																																																																																																																																																																																																											
		0010010	12h	-0.9	0101110	2Eh	-2.3	1001010	4Ah	-3.7																																																																																																																																																																																																																																																																																																																											
		0010011	13h	-0.95	0101111	2Fh	-2.35	1001011	4Bh	-3.75																																																																																																																																																																																																																																																																																																																											
		0010100	14h	-1	0110000	30h	-2.4	1001100	4Ch	-3.8																																																																																																																																																																																																																																																																																																																											
		0010101	15h	-1.05	0110001	31h	-2.45	1001101	4Dh	-3.85																																																																																																																																																																																																																																																																																																																											
		0010110	16h	-1.1	0110010	32h	-2.5	1001110	4Eh	-3.9																																																																																																																																																																																																																																																																																																																											
		0010111	17h	-1.15	0110011	33h	-2.55	1001111	4Fh	-3.95																																																																																																																																																																																																																																																																																																																											
		0011000	18h	-1.2	0110100	34h	-2.6	1010000	50h	-4																																																																																																																																																																																																																																																																																																																											
		0011001	19h	-1.25	0110101	35h	-2.65	other		-4																																																																																																																																																																																																																																																																																																																											
		0011010	1Ah	-1.3	0110110	36h	-2.7																																																																																																																																																																																																																																																																																																																														
		0011011	1Bh	-1.35	0110111	37h	-2.75																																																																																																																																																																																																																																																																																																																														
Restriction																																																																																																																																																																																																																																																																																																																																					

R82H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
VDCS	W	0	1	0	0	0	0	0	1	0	82H
1 st Parameter	W	1	-	VDCS[6]	VDCS[5]	VDCS [4]	VDCS [3]	VDCS [2]	VDCS [1]	VDCS [0]	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command defines as: This command set the VCOM DC value. Driver will base on this value for VCM_DC. 1 st Parameter:									
	Bit	Name	Description							
	6-0	VDCS[6:0]	VCOM value							
VDCS [6:0]			Voltage(V)	VDCS [6:0]	Voltage(V)	VDCS [6:0]	Voltage(V)			
0000000			00h	0(default)	0011100	1Ch	-1.4	0111000	38h	-2.8
0000001			01h	-0.05	0011101	1Dh	-1.45	0111001	39h	-2.85
0000010			02h	-0.1	0011110	1Eh	-1.5	0111010	3Ah	-2.9
0000011			03h	-0.15	0011111	1Fh	-1.55	0111011	3Bh	-2.95
0000100			04h	-0.2	0100000	20h	-1.6	0111100	3Ch	-3
0000101			05h	-0.25	0100001	21h	-1.65	0111101	3Dh	-3.05
0000110			06h	-0.3	0100010	22h	-1.7	0111110	3Eh	-3.1
0000111			07h	-0.35	0100011	23h	-1.75	0111111	3Fh	-3.15
0001000			08h	-0.4	0100100	24h	-1.8	1000000	40h	-3.2
0001001			09h	-0.45	0100101	25h	-1.85	1000001	41h	-3.25
0001010			0Ah	-0.5	0100110	26h	-1.9	1000010	42h	-3.3
0001011			0Bh	-0.55	0100111	27h	-1.95	1000011	43h	-3.35
0001100			0Ch	-0.6	0101000	28h	-2	1000100	44h	-3.4
0001101			0Dh	-0.65	0101001	29h	-2.05	1000101	45h	-3.45
0001110			0Eh	-0.7	0101010	2Ah	-2.1	1000110	46h	-3.5
0001111			0Fh	-0.75	0101011	2Bh	-2.15	1000111	47h	-3.55
0010000			10h	-0.8	0101100	2Ch	-2.2	1001000	48h	-3.6
0010001			11h	-0.85	0101101	2Dh	-2.25	1001001	49h	-3.65
0010010			12h	-0.9	0101110	2Eh	-2.3	1001010	4Ah	-3.7
0010011			13h	-0.95	0101111	2Fh	-2.35	1001011	4Bh	-3.75
0010100			14h	-1	0110000	30h	-2.4	1001100	4Ch	-3.8
0010101			15h	-1.05	0110001	31h	-2.45	1001101	4Dh	-3.85
0010110			16h	-1.1	0110010	32h	-2.5	1001110	4Eh	-3.9
0010111			17h	-1.15	0110011	33h	-2.55	1001111	4Fh	-3.95
0011000			18h	-1.2	0110100	34h	-2.6	1010000	50h	-4
0011001			19h	-1.25	0110101	35h	-2.65	other	-4	
0011010			1Ah	-1.3	0110110	36h	-2.7			
0011011			1Bh	-1.35	0110111	37h	-2.75			
Restriction										

R83H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
PTL	W	0	1	0	0	0	0	0	1	1	83H
1 st Parameter	W	1	-	-	-	PTH_ENB	-	-	HRST[9]	HRST[8]	00h
2 nd Parameter	W	1	HRST[7]	HRST[6]	HRST[5]	HRST[4]	HRST[3]	HRST[2]	-	-	00h
3 rd Parameter	W	1	-	-	-	-	-	-	HRED[9]	HRED[8]	00h
4 th Parameter	W	1	HRED[7]	HRED[6]	HRED[5]	HRED[4]	HRED[3]	HRED[2]	-	-	00h
5 th Parameter	W	1	-	-	-	-	-	-	VRST[9]	VRST[8]	00h
6 th Parameter	W	1	VRST[7]	VRST[6]	VRST[5]	VRST[4]	VRST[3]	VRST[2]	VRST[1]	VRST[0]	00h
7 th Parameter	W	1	-	-	-	-	-	-	VRED[9]	VRED[8]	00h
8 th Parameter	W	1	VRED[7]	VRED[6]	VRED[5]	VRED[4]	VRED[3]	VRED[2]	VRED[1]	VRED[0]	00h
9 th Parameter	W	1	-	-	-	-	-	-	-	PMODE	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-This command sets partial window.	
	Name	Description
	HRST[9:2]	Horizontal start address
	HRED[9:2]	Horizontal end address. HRED must be greater than HRST.
	VRST[9:0]	Vertical start address.
	VRED[9:0]	Vertical end address. VRED must be greater than VRST.
	PMODE	0: disable partial mode(default) 1: enable partial mode
	PTH_ENB	0:Source output enable follow HRST and HRED 1:Source output disable

	Note: No matter HRST[1:0] ,HRST[9:8],HRED[9:8],VRST[9:8],VRED[9:8] value being filled, it's always be 00b. No matter HRED[1:0] value being filled, it's always be 11b. Gates scan both inside and outside of the partial window. Note :No matter PTH_ENB setting , master/slave need define partial window
Restriction	

R90H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
PGM	W	0	1	0	0	1	0	0	0	0	90H

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command define as follows: After this command is issued, the chip would enter the program mode. The mode would return to standby by hardware reset.
Restriction	

R91H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
APG	W	0	1	0	0	1	0	0	0	1	91H



NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command define as follows: After this command is transmitted, the programming state machine would be activated.
Restriction	The BUSY flag would change state from 0 to 1 while the programming is completed.

R92H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
RMTP	W	0	1	0	0	1	0	0	1	0	92H
1 st Parameter	R	1	Dummy								-
2 nd Parameter	R	1	The data of address 0x000 in the MTP								-
3 rd Parameter	R	1	The data of address 0x001 in the MTP								-
4 th Parameter	R	1	:								-
5 th Parameter	R	1	The data of address (n-1) in the MTP								-
6 th ~(m-1) th Parameter	R	1									-
m th Parameter	R	1	The data of address (n) in the MTP								-

NOTE: "-" Don't care, can be set to VDD or GND level

Description	-The command define as follows: The command is used for reading the content of MTP for checking the data of programming. The value of (n) is depending on the amount of programmed data, the max address = 0x17FF
-------------	--




Restriction This command only activates when BUSY_N = "1".

RA2H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
PGM_CFG	W	0	1	0	1	0	0	0	1	0	A2H
1 st Parameter	W	1	-	-	-	VMTPSEL	-	-	M_dis	S_dis	00h
2 nd Parameter	W	1	PGM_SADDR[15:8]								00h
3 rd Parameter	W	1	PGM_SADDR[7:0]								00h
4 th Parameter	W	1	PGM_DSIZE[15:8]								0Fh
5 th Parameter	W	1	PGM_DSIZE[7:0]								00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	This command is used for setting configuration of MTP		
	1 st Parameter:		
	Bit	Name	Description
	0	S_dis	0: slave enable some command (default) 1: slave disable some command
	1	M_dis	0: master enable some command (default) 1: master disable some command
	4	VMTPSEL	0: External VMTP (default) 1: Internal VMTP
	Bit[0] enable/disable some command when IC sets slave (MS pin is low) Bit[1] enable/disable some command when IC sets master (MS pin is high)		
	Note: Some command define: R00H(Parameter 1) (PSR), R10H(DTM), R90H(PGM), R91H(APG), R83H(PTLW)		
	Command read		
	M_dis	S_dis	Description
	0	0	command read from master
	0	1	command read from master
	1	0	command read from slave
	1	1	command read from slave
2 nd & 3 rd Parameters: Program and Read MTP start address PGM_SADDR[15:0] 4 th & 5 th Parameters: Program data size PGM_DSIZE[15:0]			
Note: If user program Area0 (0x00~0x017F), PGM_SADDR[15:0] will be set 0x0000, PGM_DSIZE[15:0] will be set 0x0180.			





RE0H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
CCSET	W	0	1	1	1	0	0	0	0	0	E0H
1 st Parameter	W	1	-	-	-	-	-	-	TSFIX	CCEIN	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	This command is used for cascade.		
	1 st Parameter:		
	Bit	Name	Description
	0	CCEIN	Output clock enable/disable. 0: for single mode. (default) 1: for cascade mode.
	1	TSFIX	Let the value of slave's temperature is same as the master's. 0: Temperature value is defined by internal temperature sensor/external LM75. (default) 1: Temperature value is defined by TS_SET [7:0] registers.
Restriction			

RE3H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
PWS	W	0	1	1	1	0	0	0	1	1	E3H
1 st Parameter	W	1	VCOM_W[3:0]				SD_W[3:0]				00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	- This command is set for saving power during refreshing period. If the output voltage of VCOM / Source is from negative to positive or from positive to negative, the power saving mechanism will be activated. The active period width is defined by the following two parameters. VCOM_W: VCOM power saving width (unit = line period)  SD_W: Source power saving width (unit = 500nS), SD_W ≤ S2G 
Restriction	

RE4H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
LVSEL	W	0	1	1	1	0	0	1	0	0	E4H
1 st Parameter	W	1	-	-	-	-	-	-	LVD_SEL[1:0]		03h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	LVD_SEL[1:0]: Low Power Voltage Selection <table border="1"> <thead> <tr> <th>LVD_SEL[1:0]</th><th>LVD value</th></tr> </thead> <tbody> <tr> <td>00</td><td>< 2.2 V</td></tr> <tr> <td>01</td><td>< 2.3 V</td></tr> <tr> <td>10</td><td>< 2.4 V</td></tr> <tr> <td>11</td><td>< 2.5 V (default)</td></tr> </tbody> </table>	LVD_SEL[1:0]	LVD value	00	< 2.2 V	01	< 2.3 V	10	< 2.4 V	11	< 2.5 V (default)
LVD_SEL[1:0]	LVD value										
00	< 2.2 V										
01	< 2.3 V										
10	< 2.4 V										
11	< 2.5 V (default)										
Restriction											

RE5H	Bit										
Inst/Para	R/W	D/CX	D7	D6	D5	D4	D3	D2	D1	D0	Code
CCS_sel	W	0	1	1	1	0	0	1	0	1	E5H
1 st Parameter	W	1	-	-	-	-	cascade_sync	-	-	-	00h

NOTE: "-" Don't care, can be set to VDD or GND level

Description	This command is used for cascade.		
	1 st Parameter:		
	Bit	Name	Description
	3	cascade_sync	0: cascade mode: sync_C / TSCL / TSDA (default) 1: cascade mode: sync_C / sync_D / sync_E
Restriction			

8. OPTICAL SPECIFICATIONS

Measurements are made with that the illumination is under an angle of 45 degrees, the detection is perpendicular unless otherwise specified.


Symbol	Parameter	Condition	Min.	Typ.	Max.	Unit	Note
R	White Reflectivity	White	30	35	-	%	8-1
CR	Contrast Ratio	Indoor	8:1		-		8-2
T update	Image update time	At 25℃		16	-	sec	
Life		Topr		1,000,000 times or 5 years			

Notes:

8-1: Luminance meter: Eye-One Pro Spectrophotometer.

8-2: CR=Surface Reflectance with all white pixel/Surface Reflectance with all black pixels.

9. TYPICAL APPLICATION CIRCUIT



Part Name	Requirements for spare parts
C1—C12	0603/0805; X5R/X7R; Voltage Rating: $\geq 25V$
R1, R2	0603/0805; 1% variation, $\geq 0.05W$
D1—D3	MBR0530: 1) Reverse DC Voltage $\geq 30V$; 2) $I_o \geq 500mA$; 3) Forward voltage $\leq 430mV$
Q1	Si1308EDL: 1) Drain-Source breakdown voltage $\geq 30V$; 2) $V_{gs(th)} \leq 1.5V$; 3) $R_{ds(on)} \leq 400m\Omega$
L1	Refer to NR3015: $I_o = 500mA(max)$
P1	24pins, 0.5mm pitch

10. RELIABILITY TEST

No.	Test Items	Test Conditions
1	Low-Temperature Storage	T= -25°C, 240h Test in white pattern
2	High-Temperature Storage	T= 60°C, RH=35%, 240h Test in white pattern
3	High-Temperature Operation	T= 40°C, RH=35%, 240h
4	Low-Temperature Operation	0°C, 240h
5	High-Temperature, High-Humidity Operation	T= 40°C, RH=80%, 240h
6	High-Temperature, High-Humidity Storage	T= 50°C, RH=90%, 240h Test in white pattern
7	Temperature Cycle	1 cycle: [-25°C 30min] → [+60°C 30min]: 50 cycles Test in white pattern
8	UV exposure Resistance	765W/m ² for 168hrs, 40°C Test in white pattern
9	ESD Gun	Air+/-15KV; Contact+/-8KV (Test finished product shell, not display only) Air+/-8KV; Contact+/-6KV (Naked EPD display, no including IC and FPC area) Air+/-4KV; Contact+/-2KV (Naked EPD display, including IC and FPC area)


Notes:

Put in normal temperature for 1 hour after test finished. The display performance is OK.

11. INSPECTION METHOD AND CONDITION

11.1 INSPECTION CONDITION


Item	Condition
Illuminance	800~1500lux
Temperature	22°C ± 3°C
Humidity	55 ± 10%RH
Distance	≥30cm
Angle	Vertical fore and aft 45
Inspection method	By eyes



11.2 ZONE DEFINITION


- A Zone: Active area
- B Zone: Border zone
- C Zone: From B zone edge to panel edge


Panel edge





11.3 GENERAL INSPECTION STANDARDS FOR PRODUCTS


11.3.1 Appearance Inspection Standards

Inspection item	Figure	A zone inspection standard	B/C zone	Inspection method	MAJ/ MIN
Spot defects	Diameter $D=(L+W)/2$ (L-length, W-width) Measuring method shown in the figure below  $D = (L + W) / 2$ The distance between the two spots should not be less than 10mm	7.5"-13.3"Module (Not include 7.5") : $D > 1mm$ N=0 $0.5 < D \leq 0.8$ N≤4 Ignore $0.8 < D \leq 1$ N≤2 4.2"-7.5"Module (Not include 4.2") : $D > 0.5$ N=0 $0.4 < D \leq 0.5$ N≤2 Ignore $0.25 < D \leq 0.4$ N≤4 Module below 4.2": $D > 0.5$ N=0 $0.4 < D \leq 0.5$ N≤1 $D \leq 0.25$ Ignore $0.25 < D \leq 0.4$ N≤4 $0.1mm < D \leq 0.25$ N≤3/cm²	Foreign matter D≤1mm Pass	Check by eyes Film gauge	MIN

Inspection item	Figure	A zone inspection standard	B/C zone	Inspection method	MAJ/ MIN
Line defects	L-Length, W-Width, (W/L) < 1/4 Judged by line, (W/L) ≥ 1/4 Judged by dot  The distance between the two lines should not be less than 5mm	7.5"-13.3"Module (Not include 7.5") : $L > 10mm, N=0$ $W > 0.8mm, N=0$ $5mm \leq L \leq 10mm, 0.5mm \leq W \leq 0.8mm$ N≤2 $L \leq 5mm, W \leq 0.5mm$ Ignore 4.2"-7.5"Module (Not include 4.2") : $L > 8mm, N=0$ $W > 0.2mm, N=0$ $2mm \leq L \leq 8mm, 0.1mm \leq W \leq 0.2mm$ N≤4 $L \leq 2mm, W \leq 0.1mm$ Ignore Module below 4.2": $L > 5mm, N=0$ $W > 0.2mm, N=0$ $2mm \leq L \leq 5mm, 0.1mm \leq W \leq 0.2mm$ N≤4 $L \leq 2mm, W \leq 0.1mm$ Ignore	Ignore	Check by eyes Film gauge	MIN

Inspection item		Figure	Inspection standard	Inspection method	MAJ/ MIN
Panel chipping and crack defects	TFT panel chipping	X the length, Y the width, Z the chipping height, T the thickness of the panel 崩角  崩边 	Chipping at the edge: Module over 7.5" (Include 7.5") : $X \leq 6mm, Y \leq 1mm$ $Z \leq T$ N=3 Allowed Module below 7.5"(Not include 7.5"): $X \leq 3mm, Y \leq 1mm$ $Z \leq T$ N=3 Allowed Chipping on the corner: IC side $X \leq 2mm$ $Y \leq 2mm$, Non-IC side $X \leq 1mm$ $Y \leq 1mm$. Allowed Note: Chipping should not damage the edge wiring. If it does not affect the display, allowed	Check by eyes、 Film gauge	MIN
	Crack	 玻璃裂纹	Crack at any zone of glass , Not allowed	Check by eyes、 Film gauge	MIN
	Burr edge		No exceed the positive and negative deviation of the outline dimensions $X+Y \leq 0.2mm$ Allowed	Calliper	MIN
	Curl of panel	 H Curl height	Curl height $H \leq$ Total panel length 1% Allowed	Check by eyes	MIN

Inspection item		Figure	Inspection standard	Inspection method	MAJ / MIN
PS defect	Water proof film		1. Waterproof film damage, wrinkled, open edge, not allowed 2. Exceeding the edge of module (according to the lamination drawing) Not allowed 3. Edge warped exceeds height of technical file, not allowed	Check by eyes	MIN
RTV defect	Adhesive effect		Adhesive height exceeds the display surface, not allowed 1. Overflow, exceeds the panel side edge, affecting the size, not allowed 2. No adhesive at panel edge $\leq 1\text{mm}$, no exposure of wiring, allowed 3. No adhesive at edge and corner $1*1\text{mm}$, no exposure of wiring, allowed Protection adhesive, coverage width within $W \leq 1.5\text{mm}$, no break of adhesive, allowed	Check by eyes	MIN
	Adhesive re-fill		Dispensing is uniform, without obvious concave and breaking, bubbling and swell, not higher than the upper surface of the PS, and the diameter of the adhesive re-filling is not more than 8mm, allowed	Check by eyes	MIN
EC defect	Adhesive bubble		1. Effective edge sealing area of hot melt products $\geq 1/2$ edge sealing area; 2. Bubble $a+b \geq 1/2$ effective width, $N \leq 3$, spacing $\geq 5\text{mm}$, allowed No exposure of wiring, allowed	Check by eyes	MIN

Inspection item		Figure	Inspection standard	Inspection method	MAJ / MIN
EC defect	Adhesive effect		1. Overflow, exceeds the panel side edge, affecting the size, not allowed 2. No adhesive at panel edge $\leq 1\text{mm}$, no exposure of wiring, allowed 3. No adhesive at edge and corner $1*1\text{mm}$, no exposure of wiring, allowed 4. Adhesive height exceeds the display surface, not allowed	Visual, caliper	MIN
Silver dot adhesive defect	Silver dot adhesive		1. Single silver dot dispensing amount $\geq 1\text{mm}$, allowed 2. One of the double silver dot dispensing amount is $\geq 1\text{mm}$ and the other has adhesive (no reference to 1mm) Allowed	Visual	MIN
			Silver dot dispensing residue on the panel $\leq 0.2\text{mm}$, allowed	Film gauge	MIN
FPC defect	FPC wiring		FPC, TCP damage / gold finger peroxidation, adhesive residue, not allowed	Visual	MIJ
	FPC golden finger		The height of burr edge of TCP punching surface $\cong 0.4\text{mm}$, not allowed	Caliper	MIN
	FPC damage/cr ease		Damage and breaking, not allowed Crease does not affect the electrical performance display, allowed	Check by eyes	MIN

Inspection item		Figure	Inspection standard	Inspection method	MAJ/ MIN
Protective film defect	Protective film		Scratch and crease on the surface but no affect to protection function, allowed	Check by eyes	MIN
			Adhesive at edge $L \leq 5\text{mm}$, $W \leq 0.5\text{mm}$, $N=2$, no entering into viewing area	Check by eyes	MIN
Stain defect	Stain		If stain can be normally wiped clean by $> 99\%$ alcohol, allowed	Visual	MIN
Pull tab defect	Pull tab		The position and direction meet the document requirements, and ensure that the protective film can be pulled off.	Check by eyes/ Manual pulling	MIN
Shading tape defect	Shading tape		Tilt $\leq 10^\circ$, flat without warping, completely covering the IC.	Check by eyes/ Film gauge	MIN
Stiffener	Stiffener		Flat without warping, Exceeding the left and right edges of the FPC is not allowed. Left and right can be less than 0.5mm from FPC edge	Check by eyes	MIN
Label	Label/ Spraying code		The content meets the requirements of the work sheet. The attaching position meets the requirements of the technical documents.	Check by eyes	MIN

12. HANDLING, SAFETY, AND ENVIRONMENTAL REQUIREMENTS

WARNING

The display glass may break when it is dropped or bumped on a hard surface. Handle with care. Should the display break, do not touch the electrophoretic material. In case of contact with electrophoretic material, wash with water and soap.

CAUTION

The display module should not be exposed to harmful gases, such as acid and alkali gases, which corrode electronic components.

Disassembling the display module can cause permanent damage and invalidate the warranty agreements.

Observe general precautions that are common to handling delicate electronic components. The glass can break and front surfaces can easily be damaged. Moreover the display is sensitive to static electricity and other rough environmental conditions.

Data sheet status

Product specification	The data sheet contains final product specifications.
-----------------------	---

Limiting values

Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.

Application information

Where application information is given, it is advisory and does not form part of the specification.

Product Environmental certification

RoHS

13. PRECAUTIONS

- (1) Do not apply pressure to the EPD panel in order to prevent damaging it.
- (2) Do not connect or disconnect the interface connector while the EPD panel is in operation.
- (3) Do not touch IC bonding area. It may scratch TFT lead or damage IC function.
- (4) Please be mindful of moisture to avoid its penetration into the EPD panel, which may cause damage during operation.
- (5) If the EPD Panel / Module is not refreshed every 24 hours, a phenomena known as “Ghosting” or “Image Sticking” may occur. It is recommended to refreshed the ESL /EPD Tag every 24 hours in use case. It is recommended that customer ships or stores the ESL / EPD Tag with a completely white image to avoid this issue.
- (6) High temperature, high humidity, sunlight or fluorescent light may degrade the EPD panel’s performance. Please do not expose the unprotected EPD panel to high temperature, high humidity, sunlight, or fluorescent for long periods of time.